speco technologies®

15 Watt or 30 Watt Public Address Amplifiers

PVL15A 15W P.A. mixer amplifier

PVL30A 30W P.A. mixer amplifier

Features

- Mic1 priority mute function with front button
- Separate bass and treble controls

PVL15A

PVL30A

rear of unit

rear of unit

Specifications	PVL15A	PVL30A
RMS Output Power	15W	30W
Max. Output Power	30W	60W
AC Power Consumption	60W	100W
Power Supply	AC 120V, 50/60Hz	AC 120V, 50/60Hz
Zones	1	1
Speaker Outputs	4/8/16 Ohms, 70/25V	4/8/16 Ohms, 70/25V
Inputs	2 x Mic (1/4” and 1/4” or XLR) 1 x Aux (1/4”)	2 x Mic (1/4” and 1/4” or XLR) 1 x Aux (1/4” or RCA)
Frequency Response	50Hz ~ 15KHz	50Hz ~ 15KHz
Tone Control	Bass ± 10dB, Treble ± 10dB	Bass ± 10dB, Treble ± 10dB
THD	Less than 0.1% @1KHz	Less than 0.1% @ 1KHz
Signal/Noise Ratio	Microphone: >75dB, Line: >80dB	Microphone: >75dB, Line: >80dB
Controls	Volume for each source, Tone, Priority	Volume for each source, Tone, Priority
Telephone	No	No
Indicators	Power	Power
Dimensions	8.25” (W) x 3” (H) x 7.9” (D)	8.25” (W) x 3” (H) x 7.9” (D)
Weight	8.4 lbs.	10.6 lbs.
Listings	CE, FCC, RoHS	CE, FCC, RoHS

Speco Technologies is constantly developing and improving products.
We reserve the right to modify product design and specifications without notice
and without incurring any obligation. Spec Rev. 7/18/14