

## Open-Frame Transformers

- ST-UV16-W50Q** 16VAC/50VA
- ST-UV24-W50Q** 24VAC/50VA
- ST-UV16-W100Q** 16VAC/100VA
- ST-UVDA-W100Q** 24/28VAC/100VA
- ST-UVDA-W180Q** 24/28VAC/180VA



(Model: ST-UV16-W100Q shown)

### Features:

- Shielded windings to reduce Electromagnetic Interference (EMI).
- Selectable input voltage.
- Selectable output voltage.\*
- UL recognized.

\*ST-UVDA-W100Q and ST-UVDA-W180Q only.



### Technical Specifications:

Model	Output Voltage	Amperage	VA	Input Voltage
ST-UV16-W50Q	16VAC	3.12	50VA	120/240 VAC 50/60Hz
ST-UV24-W50Q	24VAC	2.08	50VA	120/240 VAC 50/60Hz
ST-UV16-W100Q	16VAC	6.25	100VA	120/240 VAC 50/60Hz
ST-UVDA-W100Q	24VAC	4.16	100VA	120/240 VAC 50/60Hz
	28VAC	3.57	100VA	120/240 VAC 50/60Hz
ST-UVDA-W180Q	24VAC	7.50	180VA	120/240 VAC 50/60Hz
	28VAC	6.43	180VA	120/240 VAC 50/60Hz

## Match the ENFORCER Open-Frame Transformers with the ENFORCER Series Power Supply/Chargers

Convert low-voltage AC input power to low-voltage DC output power.

- Regulated and filtered output voltage.
- Short-circuit protection.
- Thermal protection and compensation.
- Built-in backup battery charger.
- Switches to backup battery automatically in case of power loss.
- Fused protection for battery charger.
- 2 LEDs to indicate AC power input and DC power output status.
- Compatible with lead acid or gel-type rechargeable battery.
- Reverse polarity protected.



- ST-2406-2AQ** 1.5A continuous, 6/12/24 VDC
- ST-2406-3AQ** 2.5A continuous, 6/12/24 VDC
- ST-2406-5AQ** 4.0A continuous, 6/12/24 VDC
- ST-2406-7AQ** 7.0A continuous, 6/12/24 VDC
- ST-2406-10AQ** 9.0A continuous, 6/12/24 VDC

### Transformer Selection Table:

Output voltage:	ST-2406-2AQ	ST-2406-3AQ	ST-2406-5AQ	ST-2406-7AQ	ST-2406-10AQ
6VDC	12VAC / 20VA	ST-UV24-W50Q 24VAC / 50VA	ST-UV16-W100Q 16VAC / 100VA	ST-UVDA-W180Q 24/28VAC / 180VA	ST-UVDA-W180Q 24/28VAC / 180VA
12VDC	16VAC / 40VA	ST-UVDA-W100Q 24/28VAC / 100VA	ST-UV16-W100Q 16VAC / 100VA	ST-UVDA-W180Q 24/28VAC / 180VA	ST-UVDA-W180Q 24/28VAC / 180VA
24VDC	ST-UV24-W50Q 24VAC / 50VA	ST-UVDA-W100Q 24/28VAC / 100VA	ST-UVDA-W180Q 24/28VAC / 180VA	24/28VAC / 210VA	28VAC / 350VA

### SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA, 92606  
 Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326  
 Website: www.seco-larm.com | Email: sales@seco-larm.com



Copyright 2015 © SECO-LARM U.S.A., Inc. All rights reserved.  
 The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

**SECO-LARM® ENFORCER® CRIMEBUSTER® CBASLI®**