

Security

Relay Modules

Model No.	Supply Voltage	Trigger Voltage	Relay Rating	No. of Relays
SR-2206-C5AQ Heavy duty	6/12 VDC	6/12 VDC	5A	1 (DPDT)
SR-2212-C5AQ Heavy duty	12/24 VDC	12/24 VDC	5A	1 (DPDT)
SR-1212-C2ALQ Low current, high sensitivity	12/24 VDC	3~24 VDC	2A	1 (DPDT)
SR-1212-C7ALQ Heavy duty, high sensitivity	12/24 VDC	3~24 VDC	7A	2 (SPDT)
SR-2112-C7AQ/10* Heavy-duty	12/24 VDC	12/24 VDC	7A	1 (SPDT)

Relay modules for any application where

Relays are pre-wired to easy-to-install

 Screw terminals allow easy installation without soldering or other time-consuming

Wide-selection: Choose single or dual relays, low-current or heavy-duty operation, and high-sensitivity or normal-sensitivity.
SR-2112-C7AQ/10: Ships with 10 relay

modules on a single board, with easy break-

away feature for use as individual modules.





SR-2206-C5AQ

SR-2212-C5AQ





SR-1212-C2ALQ

SR-1212-C7ALQ



SR-2112-C7AQ/10 (Sold as a breakaway 10-pack)

Specifications:

Features:

modules.

connections.

relays are required.

	SR-2206-C5AQ	SR-2212-C5AQ	SR-1212-C2ALQ	SR-1212-C7ALQ	SR-2112-C7AQ/10
Supply voltage	6/12 VDC	12/24 VDC	12/24 VDC	12/24 VDC	12/24 VDC
Trigger voltage	6/12 VDC	12/24 VDC	3~24 VDC	3~24 VDC	12/24 VDC
Voltage selection	Auto-sensing	Jumper	Auto-sensing	Jumper	Jumper
Relay type	DPDT	DPDT	DPDT	SPDT	SPDT
Relay rating	5A	5A	2A	7A	7A
Number of relays	1	1	1	2	1
Current draw	70mA@6VDC 80mA@12VDC	70mA@12VDC	15mA@12VDC 18mA@24VDC	60mA@12/24 VDC	35mA@12VDC 40mA@24VDC
Size	2 ³ / ₄ "x1 ⁷ / ₈ "x ³ / ₄ " (70x48x20mm)		2 ³ / ₄ "x1 ¹⁵ / ₁₆ "x ³ / ₄ " (70x50x20mm)	2 ³ / ₈ "x1 ⁹ / ₁₆ "x ³ / ₄ " (60x40x20mm)	1 ⁹ / ₁₆ "x1 ³ / ₁₆ "x ³ / ₄ " (40x30x20mm)

SECO-LARM[®] U.S.A., Inc.

16842 Millikan Ave, Irvine, CA 92606 Phone: 949-261-2999 | 800-662-0800 Fax: 949-261-7326 Website: <u>www.seco-larm.com</u> Email: sales@seco-larm.com Copyright 2015 © SECO-LARM U.S.A, Inc. All rights reserved. All trademarks are the property of SECO-LARM U.S.A, Inc. or their respective owners. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints. ENFORCER® SECO-LARM CRIMEBUSTER® CBA SLI

PiRelayModulesb.docx