



## RSN7050 Series Lighted Area of Refuge Sign (AlphaRefuge™)



### Architects' And Engineers' Specifications

The Lighted AlphaRefuge™ Area of Refuge sign(s) shall be Alpha Communications® RSN7050 (single sided) or RSN7050D (double sided), or approved equal.

The RSN7050 series sign(s) shall operate on 120/277vac and shall built-in battery back-up, and Red LED lights. Sign(s) shall be made of white aluminum housing with acrylic surface.

The RSN7050 series sign(s) shall be UL Listed to meet UL 924, NEC, OSHA, NFPA and Life Safety Code Illumination requirements.

Contractor shall furnish and install one (1) RSN7050 (single sided) or RSN7050D (double sided) sign to be placed by each "Area Of Refuge" location, or as directed by the local AHJs.

Contractor shall observe all local and national electrical and building codes.

### RSN7050 Series Lighted Area of Refuge Sign (AlphaRefuge™)



The Alpha Communications® RSN7050 (single sided) and RSN7050D (double sided) Lighted Area of Refuge Signs are used with the AlphaRefuge™ 2100 and 2400 Series Area of Refuge systems, and can be used with other manufacturer's ARA systems.

The RSN7050 Series signs are powered by 120/277VAC and have built-in battery back-up and Red LED Lights, to comply with the current building codes.

Typically, one RSN7050 Series sign would be placed at each "Area of Refuge" location, to identify that location for building visitors and residents, for ARA code compliance.

### Features

- Power: 120/277VAC (4w, 350 mA)
- Battery Back-up
- Red LED Lights
- Constant Uniform Illumination
- UL Listed to meet UL 924, NEC, OSHA, NFPA and Life Safety Code Illumination requirements
- Sign should be mounted above 60" but below 80" from the finished floor to the top of the sign
- White Aluminum housing with Acrylic surface
- Voltage Surge and Short Circuit protection

### Specifications

<b>Dimensions:</b>	14.00"W (356mm) x 10.50"H (267mm) x 3.00"D (77mm)
<b>Models Available:</b>	Model# <b>RSN7050</b> (single-sided) Model# <b>RSN7050D</b> (double-sided)

### Alpha Communications

42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599  
TOLL-FREE: (800) 666-4800 • Web: AlphaCommunications.com • Email: info@alphacommunications.com

Copyright© 1998-2016 Alpha Communications® - All Rights Reserved.  
Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.