



TSM Series Speaker/Microphones (For modular door stations)



Model TSMT Shown (Titanium Finish)

Architects' And Engineers' Specifications

Speaker/microphone module(s) shall be Alpha Communications® / S.T.R. $^{\text{TM}}$ (TSM 5-wire) or (TSMA 2-wire) or (TSMB 2-wire loop) or (TSMB3 2-wire QWIKBus $^{\text{TM}}$) series or approved equal. Speaker/microphone module(s) shall snap into the corresponding MT series modular panel frame(s).

Speaker/microphone module(s) shall be finished in Titanium (suffix-T), White (suffix-W), Brown (suffix-B), Silver (suffix-S), or Dark Grey (suffix DG) and shall feature a weather-resistant speaker, long life electret condenser microphone, illuminated dry contact low voltage light push button and plug-in connector for easy wiring.

Contractor shall observe all local and national electrical and building codes.

TSM / TSMA / TSMB / TSMB3 Series Speaker/Microphones for Modular Door Stations

The TSM series speaker/microphones are designed to be used with Alpha Communications $\mbox{\@modelnnthmodelness}/\mbox{\/ S.T.R.}^{\mbox{\/ M}}$ modular series door entry stations.

The TSM series is used with the standard 5-wire type apartment handsets (i.e. HT3003, HT2003, HT2006) and standard analog video-intercom systems. The TSMA series is used with the standard 2-wire type AlphaTone $^{\text{TM}}$ apartment handsets (i.e. HT3009, HT2009).

The TSMB series is used with the 2-wire (loop) type ReliaBUS $^{\text{TM}}$ apartment handsets (i.e. HT3011, HT2011).



The TSMB3 series is used with the 2-wire (loop) type QwikBUS[™] apartment handsets (i.e. HT3033, HT40, HT45).

All TSM speaker/microphone modules feature a weather-resistant speaker, long-life electret condenser microphone, illuminated drycontact low voltage light pushbutton and plug-in connector for easy wiring.

All TSM speaker/microphone modules are now available in five (5) attractive finishes; Titanium (suffix-T), White (suffix-W), Brown (suffix-B), Silver (suffix-S) or Dark Grey (suffix-DG).

All TSM speaker/microphone modules are 3.94"w x 3.94"h (100mm x 100mm), and are made to snap into the MT series modular panel trim frame(s).

To service the TSM series modules, once installed, use the model 13510 key / tool unit

42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599
TOLL-FREE: (800) 666-4800 • Web: AlphaCommunications.com • Email: info@alphacommunications.com