

# WDL-1900PVM-IP

## 19" IP Public View Monitor

- 19" 5:4 (1280 x 1024) LCD Panel
- Built-in WDR full HD camera (1920 x 1080 FHD)
- Multiple video inputs - 3 CVBS (BNC), D-SUB, HDMI, DVI-D
- Analog video output - 3 x CVBS loopout (BNC)
- 3D comb filter
- Supported ONVIF profile S/version 2.2
- Fully Integrated with Verint, March Networks, & 3VR.
- Changeable logo clip / video clip (SD memory)



LCD

19"

1000:1

250  
(cd/m<sup>2</sup>)

1280  
x  
1024



## Specification

Display	Screen size	19"
	Resolution	1280 x 1024
	Brightness	250 cd/m <sup>2</sup>
	Contrast ratio	1000 : 1
	Response time	5ms (max 8ms)
	Viewing angle	170(H) / 160(V)
	Aspect ratio	5:4
Camera	Image sensor	1/2.8" SONY 2.38M progressive C-MOS
	Lens	2.9mm fixed lens
	Active pixel	1920 (H) x 1080 (V)
	Frame rate	30 fps
	Backlight compensation	WDR [HDR]

## Specification

Camera	Compression	H.264 @HP, MJPEG
	Streaming	Simultaneous multiple streams H.264 streaming over UDP,TCP,HTTP or HTTPS MJPEG streaming over HTTP or HTTPS
	Resolution	1920x1080
	Frame rate	up to 30fps @ 1080p
	Interface	10/100 Mbps Ethernet, RJ-45
	ONVIF	PROFILE S / version 2.2 support
	Protocols pixel	IPv4, TCP/IP, HTTP, HTTPS, UPnP, BONJOUR RTP/RTSP, SMTP, FTP, DHCP, NTP, DNS, DDNS, SNMP
	Users	8 clients monitoring at the same time
	Security	Multi-level user access with password protection IP address filtering HTTPS encrypted data transmission
	Firmware	Supports firmware upgrade
	Dual booting	Support for firmware recovery
	Factory reset	Restores to factory default settings
	Operation system	Embedded linux
Video output (CVBS)	CVBS monitor output	CVBS (BNC)
	Camera loopout	CVBS (BNC)
Video input	CVBS	NTSC/PAL multi (BNC 75Ohm)
	Analog RGB (PC VGA)	D-SUB15P connector
	DVI	DVI-D connector
	HDMI	HDMI connector
Power	Power input	DC12V/5A
	Power consumption	T.B.D
	Power output	12V/0.5A (for external camera)
Environmental	Operating temperature	0° C ~ +50° C
	Humidity	10 ~ 90% RH, non condensing
Dimensions	Outline dimension (mm)	-
	Weight	-
Media Player	File format	-

## Dimension

