



T-7722VD Extra Features 2Plus Wall Handset (Golmar)



Architects' And Engineers' Specifications

The 2-Wire handset station(s) shall be Alpha Communications® / Golmar T-7722VD or approved equal. Handset(s) shall be mounted (surface or desktop with optional SOB-700 adapter). Handset(s) shall feature electret condenser microphone for exceptional voice fidelity. Handsets that include carbon transmitter or other voice technologies shall not be acceptable. Handset shall have a heavyduty replaceable coil cord. Handset shall include a door release pushbutton and auxiliary pushbutton. Handset(s) shall include a built-in electronic call tone signal. Handset(s) shall require only two (2) common (loop) wires for system operation.

Contractor shall observe all local and national electrical and building codes.

T-7722VD Series Handsets

The Alpha Communications® / Golmar T-7722VD Series handsets are designed to work as an apartment type handset intercom station, using a minimal of wiring. All T-7722VD handsets in a building can be wired typically on only two (2) common (loop) wires!

These attractive handsets easily surface mount right on the wall. Handsets can be changed to desk mount with the addition of a model SOB-700 desk adapter, or can be used with the addition of a model MAC-500 plastic adapter trim plate.

All T-7722VD series handsets feature electronic tone signaling, heavy duty replaceable coiled cord and (2) two momentary button switches. These switches can be used for door release, or other signalling functions, depending upon system configuration.

Features

- Crystal Clear Half-Duplex Voice Operation
- Polished ABS RAL9003 White Plastic
- Microprocessor circuitry with eeprom memory
- Easy Installation Only 2 Common (loop) Wires Required
- Privacy on audio and door open functions
- Clear Voice Fidelity using Electret Condenser Microphones
- Rugged and Reliable / Simple to Operate
- Mounts Surface or Desk (with desk adapter SOB-700)
- Two position call tone volume selector with On/Off function
- Separate input for apartment door call pushbutton
- Different call tones depending where the call is coming from (entry station or apartment entry door)
- Built-in Door Release pushbutton (can also be used to call to porter/concierge switchboard)
- Additional dry-contact momentary pushbutton

Specifications

42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599
TOLL-FREE: (800) 666-4800 • Web: AlphaCommunications.com • Email: info@alphacommunications.com