

B10R Medium Control Panel Enclosure (Red)

www.boschsecurity.com



BOSCH

Invented for life



- Easy to install standoff locations for mounting supporting modules
- Made with cold-rolled steel with a red matte finish for fire applications
- Easy access mounting locations for optional transformers
- Punch outs for optional B46 External Annunciator (for B465 only)

The B10R Medium Control Panel Enclosure is a red enclosure made of cold-rolled steel that is 1.0 mm (20 gauge) thick. It houses many different Bosch control panels and modules. The enclosure holds one 18Ah battery or two batteries (up to 7Ah).

It is compatible with the following accessories:

- **D101 Lock and Key Set.** Standard lock set with one key supplied. Uses the D102 (#1358) replacement key.
- **D110 Tamper Switch.** Screw-on tamper switch that fits all enclosures. Shipped in packages of two.
- **ICP-EZTS Dual Tamper Switch.** Combination tamper switch with a wire loop for additional tamper outputs.

Parts included

Quantity	Component
1	B10R Medium Control Panel Enclosure
1	Hardware pack
1	Installation Guide (hardcopy)

Technical specifications

Properties

Dimensions	14 in x 12.5 in x 3 in (35.6 cm x 31.8 Cm x 7.6 cm)
Material	1.0 mm (20 gauge) cold-rolled steel
Color	Red

Environmental considerations

Mounting considerations	Mount in dry indoor locations.
-------------------------	--------------------------------

Compatibility

Devices	B465 Conettix Universal Dual Path Communicator B46 External Annunciator D101 Lock and Key Set ICP-EZTS Tamper Switch Set D110 Tamper Switch
---------	---

Ordering information

B10R Medium Control Panel Enclosure (Red)

Red, steel enclosure. Accepts an optional lock and tamper switch.

Order number **B10R**

Accessories

D101 Lock and Key Set

Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.

Order number **D101**

ICP-EZTS Dual Tamper Switch

Combination tamper switch with a wire loop for additional tamper outputs.

Order number **ICP-EZTS**

D110 Tamper Switch

Screw-on tamper switch that fits all enclosures. Shipped in packages of two.

Order number **D110**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
203 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com